
Battery Charger / Maintainer





The **Battery Charger / Maintainer** enables an **extra battery bank** to be kept 'topped up' from the **main battery bank** which has the charging device(s) connected to it (e.g. alternator, battery charger, solar cell/wind turbine etc.).

The **Battery Charger / Maintainer** benefits over voltage sensitive relays by being FET based rather than relay based. This FET based device draws less than 1mA under operation. This maximises the power generated from a low charge device, such as a solar cell. Relays also have a limited life cycle due to constant physical contact. FETs are free from contact, wear and noise production increasing longevity of the device.

Sterling

Products

The **Battery Charger / Maintainer** works by detecting when the **main battery bank** reaches 13.3V and allows the excess power to be transformed to the **extra battery bank** with only a minor voltage drop of 0.2V. This allows the extra battery bank to be 'maintained' by charging it with several amps. This device is not a high charging device it's a maintenance device. For higher charging battery to battery devices read Sterling's literature on the **ProBatt C** (battery to battery charger).


Ideal places of use

Marine - domestic 12V/24V to generator 12V starter 12V/24V to domestic 12V/24V starter 12V/24V to bow thruster 24V The list / combinations are endless

Camper / RV - domestic 12V/24V to starter 12V/24V domestic 12V/24V to generator 12V

Solar / Wind top up - sharing surplus power from a solar/wind charged battery to other batteries.

Battery maintainer / charger inc 1 metre of cable					
Input V d/c	Output V d/c	Amps	Size L x W x D mm	Weight kg	Part nos
12	12	3	140 x 45 x 40	0.25	BM12123
12	24	1	140 x 45 x 40	0.25	BM12241
24	24	3	140 x 45 x 40	0.25	BM24241
24	12	1	140 x 45 x 40	0.25	BM24121





Unit 8 Wassage Way Hampton Lovett Ind Est Drotwich WR9 0NX Tel:01905 771771 Fax: 01905 779434 e mail:help@sterling-power.com web: www.sterling-power.com www.sterling-power-usa.com



