xantrex

Introduction

Thank you for purchasing the Xantrex™ PROwatt™ SW Auto Transfer Switch, an automatic AC power transfer switch that automatically switches between primary and secondary AC input sources to power a single AC output circuit. The PROwatt SW Auto Transfer Switch (part number: 808-0915) automatically toggles between AC power from the PROwatt SW inverter and AC power from another AC source such as utility or shore power to transfer to a single AC output such as a qualified load via a branch circuit.

READ THIS GUIDE BEFORE OPERATING THE PROWATT SW AUTO TRANSFER SWITCH, AND SAVE IT FOR FUTURE REFERENCE.

Important Safety Information

Misusing or incorrectly connecting the auto transfer switch may damage the equipment or create hazardous conditions for users. Read the following safety instructions and pay special attention to all Caution and Warning statements in the guide. Warnings identify conditions that may result in personal injury or loss of life. Cautions identify conditions or practices that may damage the unit or other equipment.

$oldsymbol{\Delta}$ WARNING **ELECTRICAL SHOCK HAZARD**

- Keep the auto transfer switch out of reach of children and pets.
- Do not expose the auto transfer switch to moisture, rain, spray, or snow. For marine application, use a drip shield.
- Do not operate the auto transfer switch if it has been damaged in any way.
- Do not disassemble the auto transfer switch. There are no user-serviceable parts inside.

Failure to follow these instructions can result in death or serious injury.


△CAUTION **EQUIPMENT DAMAGE**

30% of switch rating.

- Use with Xantrex PROwatt SW Inverter only
- Not intended for use with parallel
- engine generator (sets). Tungsten filament load not to exceed

Failure to follow these instructions can result in equipment damage.

Features



Installation/Operation

- Disconnect or turn off all power sources prior to installation
- Connect the AC Output cable to an input branch circuit such as a load sub-panel in your RV or motor home. NOTE: Use a qualified installer or technician if you don't have sufficient knowledge on how to connect to a branch circuit. Consult your RV/motor home/boat dealer for guidance.
- Connect the AC Input 1 cable to your PROwatt SW inverter.
- Connect the AC Input 2 cable to an output branch circuit such as a utility sub-panel in your RV or motor home. NOTE: Use a qualified installer or technician if you don't have sufficient knowledge on how to connect to a branch circuit. Consult your RV/motor home/boat dealer for guidance.
 5. Turn on all power sources.

Specifications

NOTE: Specifications are subject to change without notice.

AC input voltage and frequency	120 VAC 60 Hz
AC input current	15 A (max)
AC output voltage and frequency	120 VAC 60 Hz
AC output current	15 A (max)
Transfer time	80 ms
Dimensions (L×W×H)	96×75×70 mm 3 ²⁵ / ₃₂ ×2 ³⁰ / ₃₂ ×2 ²⁴ / ₃₂ in.
Weight	0.64 kg (1.4 lbs.)

Warranty and Return Information

Warranty

What does this warranty cover? This Limited Warranty is provided by Xantrex Technology Inc. ("Xantrex") and covers defects in workmanship and materials in your PROwatt SW Auto Transfer Switch. This warranty period lasts for 3 months/mois/meses from the date of purchase at the point of sale to you, the original end user customer, unless otherwise agreed in writing (the "Warranty Period"). You will be required to demonstrate proof of purchase to make warranty claims.

This Limited Warranty is transferable to subsequ owners but only for the unexpired portion of the Warranty Period. Subsequent owners also require original proof of purchase as described in "What proof of purchase is required?"

What will Xantrex do? During the Warranty Period

What will Xantrex do? During the Warranty Period Xantrex will, at its option, repair the product (if economically feasible) or replace the defective product free of charge, provided that you notify Xantrex of the product defect within the Warranty Period, and provided that Xantrex through inspection establishes the existence of such a defect and that it is covered by this Limited Warranty. Xantrex will, at its option, use new and/or reconditioned parts in performing warranty repair and

Aantrex wiii, at its option, use new and/or reconditioned parts in performing warranty repair and building replacement products. Xantrex reserves the right to use parts or products of original or improved design in the repair or replacement. If Xantrex repairs or replaces a product, its warranty continues for the remaining portion of the original Warranty Period or 90 days from the date of the return shipment to the customer, whichever is greater. All replaced products customer, whichever is greater. All replaced products and all parts removed from repaired products become the property of Xantrex.

Xantrex covers both parts and labor necessary to repair the product, and return shipment to the customer via a Xantrex selected non-expedited surface freight within the contiguous United States and Canada. Alaska, Hawaii and outside of the United States and Canada are excluded. Contact Xantrex Customer Service for details on freight policy for return shipments from

How do you get service? If your product requires How do you get service? If your product requires troubleshooting or warranty service, contact your merchant. If you are unable to contact your merchant, or the merchant is unable to provide service, contact Xantrex directly at: 1408 897 6359 (direct telephone) or customerservice@xantrex.com (Email). Direct returns may be performed according to the Xantrex Return Material Authorization Policy described in your product manual. For some products, Xantrex maintains a network of regional Authorized Service Centers. Call Xantrex or check our website to Service Centers. Call Xantrex or check our website to see if your product can be repaired at one of these

Mat proof of purchase is required? In any warranty claim, dated proof of purchase must accompany the product and the product must not have been disassembled or modified without prior written authorization by Xantrex.

Proof of purchase may be in any one of the following

- The dated purchase receipt from the original purchase of the product at point of sale to the end
- The dated dealer invoice or purchase receipt showing original equipment manufacturer (OEM) status; or

original equipment manufacturer (OEM) status; or

• The dated invoice or purchase receipt showing the
product exchanged under warranty.

What does this warranty not cover? Claims are
limited to repair and replacement, or if in Xantrex's
discretion that is not possible, reimbursement up to the
purchase price paid for the product. Xantrex will be
liable to you only for direct damages suffered by you
and only up to a maximum amount equal to the
purchase price of the product.

This Limited Warranty does not warrant uninterrupted
or errorfree operation of the product or cover normal
wear and tear of the product or costs related to the
removal, installation, or troubleshooting of the
customer's electrical systems. This warranty does not

customer's electrical systems. This warranty does not apply to and Xantrex will not be responsible for any

defect in or damage to:
a) the product if it has been misused, neglected,
improperly installed, physically damaged or altered,
either internally or externally, or damaged from

either internally or externally, or damaged from improper use or use in an unsuitable environment; b)the product if it has been subjected to fire, water, generalized corrosion, biological infestations, or input voltage that creates operating conditions beyond the maximum or minimum limits listed in the Xantrex product specifications including but not limited to high input voltage from generators and lightning strikes; c) the product if repairs have been done to it other than by Xantrex or its authorized service centers (hereaf-

by Xantrex or its authorized service centers (hereaf-

d) the product if it is used as a component part of a product expressly warranted by another manufac-

turer;
e) component parts or monitoring systems supplied by you or purchased by Xantrex at your direction for incorporation into the product;
f) the product if its original identification (trade-mark,

serial number) markings have been defaced, altered, or removed; g) the product if it is located outside of the country

where it was purchased; and h) any consequential losses that are attributable to the product losing power whether by product malfunc-tion, installation error or misuse.

Product Disclaimer

TION, INSTALLATION CHOICAGE

PRODUCT DISCIGNIENE
THIS LIMITED WARRANTY IS THE SOLE AND EXCLUSIVE
WARRANTY PROVIDED BY XANTREX IN CONNECTION
WITH YOUR XANTREX PRODUCT AND IS, WHERE
PERMITTED BY LAW, IN LIEU OF ALL OTHER
WARRANTIES, CONDITIONS, GUIRANTIES,
REPRESENTATIONS, OBLIGATIONS AND LIABILITIES,
EXPRESS OR IMPLIED, STATUTORY OR OTHERWISE IN
CONNECTION WITH THE PRODUCT, HOWEVER ARISING
(WHETHER BY CONTRACT, TORT, NEGLIGENCE,
PRINCIPLES OF CONTRACT
WHETHER BY CONTRACT, TORT, NEGLIGENCE,
PRINCIPLES OF CONTRACT
WHETHER BY CONTRACT
WHETHER BY CONTRACT
WHETHER STATUTORY OR OTHERWISE;
NICLUDING WITHOUT RESTRICTION ANY IMPLIED
WARRANTY OR CONDITION OF QUALITY,
WERCHANTABILITY OR FITNESS FOR A PARTICULAR
PURPOSE ANY IMPLIED WARRANTY OF
WISCHANTABILITY OR FITNESS FOR A PARTICULAR
PURPOSE TO THE EXTENT REQUIRED UNDER
APPLICABLE LAW TO APPLY TO THE PRODUCT SHALL BE
LIMITED IN DURATION TO THE PERIOD STIPULATED
UNDER THIS LIMITED WARRANTY, IN NO EVENT WILL
XANTREX BE LIABLE FOR: (A) ANY SPECIAL, INDIRECT,
INCIDENTIAL OR CONSEQUENTIAL DAMAGES, INCLUDING
LOST PROFITS, LOST REVENUES, FAILURE TO REALIZE
EXPECTED SAYINGS, OR OTHER COMMERCIAL RE
BEEN ADVISED, OR THAD REASON TO KNOW, OF THE
DOSSIBILITY OF SUCH DAMAGE; (B) ANY LIABILITY
ARISING IN TORT, WHETHER OR NOT ARISING OUT OF
XANTREYS NEGLIGENCE, AND ALL LOSSES OR DAMAGES
TO ANY PROPERTY OR FOR ANY PERSONAL INJURY OR
ECONOMIC LOSS OR DAMAGE CAUSED BY THE
CONNECTION OF A PRODUCT TO ANY OTHER DEVICE OR
SYSTEM; AND (C) ANY DAMAGE OR ABUSE OR THE
CONNECTION OF A PRODUCT TO ANY OTHER DEVICE OR
SYSTEM; AND (C) ANY DAMAGE OR ABUSE ON TO REATION
OF THE PRODUCT BY PERSONS NOT AUTHORIZED BY
XANTREXS.

LATUSONS

IF THIS PRODUCT IS A CONSUMER PRODUCT, FEDERAL LAW DOES NOT ALLOW AN EXCLUSION OF IMPLIED WARRANTIES. TO THE EXTENT YOU ARE ENTITLED TO MANDANTIES. UNDER FEDERAL LAW, TO THE EXTENT PERMITTED BY APPLICABLE LAW THEY ARE LIMITED TO THE DURATHON OF THIS LIMITED WARRANTY. SOME STATES, PROVINCES AND JURISDICTIONS DO NOT ALLOW LIMITATIONS OR EXCLUSIONS ON IMPLIED

WARRANTIES OR ON THE DURATION OF AN IMPLIED WARRANTY OR ON THE LIMITATION OR EXCLUSION OF WARANTT ON THE LIBITATION OF INCIDENTAL OR CONSEQUENTIAL DAMAGES, SO THE ABOVE LIMITATION(S) OR EXCLUSION(S) MAY NOT APPLY TO YOU. THIS LIMITED WARRANTY GIVES YOU SPECIFIC LEGAL RIGHTS. YOU MAY HAVE OTHER RIGHTS WHICH MAY VARY FROM STATE TO STATE, PROVINCE TO PROVINCE OR JURISDICTION TO JURISDICTION.

Return Material Authorization Policy

Before returning a product directly to Xantrex you must obtain a Return Material Authorization (RMA) number and the correct factory "Ship To" address. Products must also be shipped prepaid. Product shipments will be refused and returned at your expense if they are unauthorized, returned without an RMA number clearly marked on the subsiding of the shipping. number clearly marked on the outside of the shippin box, if they are shipped collect, or if they are shipped to the wrong location.

When you contact Xantrex to obtain service, please

when you contact xantrex to obtain service, please have your instruction manual ready for reference and be prepared to supply:

The serial number of your product

Information about the installation and use of the unit

Information about the failure and/or reason for the

- A copy of your dated proof of purchase

Return Procedure

- 1. Package the unit safely, preferably using the original box and packing materials. Please ensure that your product is shipped fully insured in the original packaging or equivalent. This warranty will not apply where the product is damaged due to improper packaging.

 2. Include the following:
- The RMA number supplied by Xantrex Technology Inc. clearly marked on the outside of
- A return address where the unit can be shipped. Post office boxes are not acceptable.

 • A contact telephone number where you can be
- A contact elephone limited where you can be reached during work hours.
 A brief description of the problem.
 Ship the unit prepaid to the address provided by your Xantrex customer service representative.

If you are returning a product from outside of the USA or Canada In addition to the above, you MUST include return freight funds and are fully responsible for all documents, duties, tariffs, and deposits.

Out of Warranty Service

If the warranty period for your PROwatt SW Auto
Transfer Switch has expired, if the unit was damaged
by misuse or incorrect installation, if other conditions
of the warranty have not been met, or if no dated proof of purchase is available, your inverter may be serviced or replaced for a flat fee.

To return your PROwatt SW Auto Transfer Switch for

out of warranty service, contact Xantrex Customer Service for a Return Material Authorization (RMA) number and follow the other steps outlined in "Return Procedure" above.

Procedure above.

Payment options such as credit card or money order will be explained by the Customer Service Representative. In cases where the minimum flat fee does not apply, as with incomplete units or units with excessive damage, an additional fee will be charged. If applicable, you will be contacted by Customer Service once your unit has been received. once your unit has been received.

Once Your unit has been received.

Xantex and PROwatt are registered trademarks of Schneider Electric Services International sprl, registered in the United States and other countries. PROwatt SW Auto Transfer Switch Owner's Guide Copyright of May 2010, Xantex Echnology Inc. All rights reserved. Moreover, and the States of Copyright of May 2010, Xantex Echnology Inc. All rights reserved hide parties without the express written consent of Xantex Technology Inc. 161-G South Vasco Road, Livernore, California, USA 94551, Xantex Technology Inc. 161-G South Vasco Road, Livernore, California, USA 94551, Xantex Technology Inc. 161-G South Vasco Road, Livernore, California, USA 94551, Xantex Technology Inc. 161-G South Vasco Road, Livernore, California, USA 94551, Xantex Technology Inc. 161-G South Vasco Road, Vasco Road